

# PRICE BID

## ELECTRICAL WORK of KHOPALA BRANCH, KHOPALA, RBO-4, Ahmedabad

| Sr. No. | DESCRIPTION   | QTY | UNIT | RATE | AMOUNT |
|---------|---|-----|------|------|--------|
|         | NOTE : ALL CHARIS OR CHASES IN WALLS / COLUMNS / SLABS MADE BY THE ELECTRICAL CONTRACTOR FOR INSTALLATION OF CONDUITS / S.B. / BOXES ETC. THE FILLING OF THE SAME IS IN THE SCOPE OF THE ELECTRICAL CONTRACTOR INCLUDING ALL NECESSITY MATERIAL AND LABOUR.   |     |      |      |        |
|         | <b>PART - A ::: BRANCH</b>  |     |      |      |        |
| A       | <b>INTERNAL WIRING :Phase wire must be Red colour for LDB, Yellow colour for PDB &amp; Blue for ACDB, Neutral Wire of Black colour &amp; Green Wire for Earthing. Color code must be maintained. Tagging from DB MCB and Switch board must be done.</b>   |     |      |      |        |
| 1       | SITC of point wiring in concealed in walls, furniture's & for above false ceiling, or on ceiling, on beams shall be fixed with saddles & spacers etc., with conduits taken in slab with 20 mm dia PVC Rigid conduits 1.5 mm thick ISI mark with 2 nos. of 1.5 sq. mm. phase & nutral & 1 nos. of 1.0 sq. mm. earthing with modular switch with company made flush metal box/surface PVC box etc. comp. with nec. main lines for switch board from LDB of mains of 2 nos. of 2.5 sq.mm wire and 1 no.of 1.0 sqmm pvc Insulated copper conductor wire FRLS type laying in with 20 mm/25 mm dia PVC rigid conduits 1.5 mm thick ISI mark . <b>These will be used with point wiring of light, fan, ex. fan, callbell points, etc { Max. 3 Switchboards in one circuit - One Sp MCB }.Phase wire must be Red colour, Nutral Wire must be Black color &amp; Green Wire for Earthing. Color code must be maintained. Tagging from Lighting DB MCB and Switch board must be done.</b> |     |      |      |        |
| 1.1     | One 5A switch controlling one light / fan point.  | 26  | nos  |      |        |
| 1.2     | One switch controlling Two light points .   | 13  | nos  |      |        |
| 1.3     | 5A socket outlet with 5A switch ( on common board ) ( <b>1 FOR WATER COOLER</b> ).  | 12  | nos  |      |        |
| 1.4     | 5A socket outlet with 5A SP switch (as an independent point ) [ <b>for ex. Fan, wall fan , QMS, Token M/C Display, etc. points.</b> ]   | 10  | nos  |      |        |
| 1.5     | Call bell point with bell push complete.  | 1   | nos  |      |        |
| 1.6     | SITC of loop light points Of <b>2 nos. of 1.5 sq. mm. off wires &amp; 1 nos. of 1.0 sq. mm. earth wire from Main panel timer</b> of mains of 2 nos. of 2.5 sq.mm wire and 1 no.of 1.0 sqmm pvc Insulated copper conductor earth wire laying in with 20 mm/25 mm dia type PVC rigid conduits 1.5 mm thick ISI mark. ( <b><u>This point is for Signage and Light Points at Entrance</u></b> ).  | 3   | nos  |      |        |
| 2.1     | SITC of 6/16 Amp. Switch and socket complete with necessary require wiring from LDB of <b>2 no of 2.5 sq mm wires and 1 no of 1.0 sq mm</b> PVC Insulated copper conductor earth wire laying in with 20 mm/25 mm dia PVC rigid conduits 1.5 mm thick ISI mark. These will be used with point wiring of power points ,etc. <b>No Looping of Neutral or earthing is allowed. Each point needs to provide seperate circuit.This Points Need to Be Connected through LDB. ( <u>For Cash Room, Locker Room, Record room - wiring points</u> ).</b>   | 3   | nos  |      |        |

**ELECTRICAL WORK of KHOPALA BRANCH, KHOPALA, RBO-4, Ahmedabad**

| Sr. No.  | DESCRIPTION  | QTY | UNIT | RATE | AMOUNT |
|----------|--|-----|------|------|--------|
| 2.2      | SITC of 6/16 Amp. Switch and socket complete with necessary require wiring from PDB of 2 no of 4.0 sq mm wires and 1 no of 2.5 sq mm PVC Insulated copper conductor earth wire laying in with 20 mm/25 mm dia PVC rigid conduits 1.5 mm thick ISI mark. These will be used with point wiring of power points ,etc. . <b>No Looping of Neutral or earthing is allowed. Each point needs to provide seperate circuit.This Points Need to Be Connected through PDB. ( For Printer, Water Cooler, Freeze, Motor, Note Counting Machine points ).</b>   | 3   | nos  |      |        |
| 3        | SITC of 20 A/ 25 A , 230 V, with DP RCCB, 100 mA all enclosed in a prefabricated M S boxes complete to the satisfaction of E.I.C. For SPLIT AC 1.5TR / 2.0 TR unit with necessary require wiring from ACDB of 2 no of 4.0 sqmm wires and 1 no of 2.5 sqmm PVC Insulated copper conductor wire FRLS type laying in with 20 mm/25 mm dia PVC rigid conduits 1.5 mm thick ISI mark. These will be used with point wiring of A.C. points ,etc . <b>Color code must be maintained. Tagging from DP MCB and AC point must be done. This point should be installed near Split / window AC in concealed manner. No Looping of Neutral or earthing is allowed. Each point needs to provide seperate circuit. The height of switchboard must be at reachable point for easily operation.from that point to Split AC,empty conduit + necessary bends must in concealed mode by ele. contractor. THE ENCLOSURE SHOULD BE SAME MAKE AS MCB MAKE.</b>      | 4   | nos  |      |        |
| <b>B</b> | <b>LIGHTING FIXTURES :</b>   |     |      |      |        |
|          | (NOTE : ANY OF FIXTURES AND FITINGS SHALL BE RE-CONFIRMED WITH THE ARCHITECTS / CONSULANTS BEFOTE ORDERING THEM.   |     |      |      |        |
| 4        | SITC of (including supply and fixing flexible wires from holder to fixtures hardwares etc.) of.... - <b>The LED lamps should be of same make as fixture make. - The marking &amp; cutting of fixtures should be in ele. contractor's scope.. fixtures should be approved by bank's ele. engineer / ele. consultant / architect. from the given make list before installations. LM 79 &amp; LM 80 test reports to be submitted. nichia / LUmileds / cree - LED should be used by manufacture. Lighting Luminaire of LED for Office single piece die cost aluminium M24 housing complete with driver unit, mirror optic and other accessories Lamps of about 100 lumen/W injection moulded PC diffusers with high brightness complete unit complying with international standard (LU49, LH801) - opertive on 190V - 270 V 50 Hz with Mini 3 years warranty complete with mounting system and lamp dully wired and tested Details as under.</b> |     |      |      |        |
| 4.1      | SITC of LED 1 x 36 W ( 3100 lumens ) ( 2' X 2') RECESS MOUNTED LUMINAIRE with 2KV surge protection, making earthing conection complete to be recessed in false ceiling with all necessary hardwares, hanging - die cast frame arrangement, chains or hook arrangement with ceiling, connected to supply wire with PVC connector. Earthing connection with lugging need to given to body of Fixture, etc. complete. (Crompton Model ORION II Cat Ref No: LCTRLN-36-FO-CDL, CCT 6000 K and CRI > 80, lumen O/P > 3300 lumen, Syatem wattage (LED + Driver) < 40 Watt. or Equivalent in GE/ Philips / Havells / Wipro make) .   | 11  | nos  |      |        |

**ELECTRICAL WORK of KHOPALA BRANCH, KHOPALA, RBO-4, Ahmedabad**

| Sr. No. | DESCRIPTION  | QTY | UNIT | RATE | AMOUNT |
|---------|--|-----|------|------|--------|
| 4.2     | SITC of 1 x 12 W Square / Round LED DOWN LIGHT pressure die cast fixture with 2KV surge protection ( 950 lumens ) to be recessed in false ceiling with all necessary hardwares, chains, hook etc. complete.( CROMPTON make cat no. Crompton Model CROM LCDD-15-CDL/TL/ WW ,CCT 6000 K and CRI > 80,Lumen output1450 lumen, System wattage( LED + Driver ) 12 Watt or Equivalent in GE / Philips / Havells / Wipro make ). <b>Energy Efficient round recessed mounted LED down lighter with premium white powder coating and die cast aluminium housing. as per details above. Die casting material should not be CRCO type material. should be connected to supply wire with PVC connector. Earthing connection with lugging need to given to body of Fixture.</b> | 23  | nos  |      |        |
| 4.3     | SITC of LED tube light 1 x10 W ( 560 lumens ) Surface mounting type with LED tube, complete. (Crompton Model : LINNET; CAT Ref No: LCL-07-CDL or Equivalent PHILIPS / GE / Wipro make ) . For Toilet area.   | 3   | nos  |      |        |
| 4.4     | Supply and insallation of Call bell with Indicatore. (Max or equivalent make)  | 1   | nos  |      |        |
| 4.5     | SITC of Exhaust fan of 300 mm, fresh air vantilator type complete & 6 Amp. 3 pin TOP. (Crompton/ Khaitan / Havells make) <b>[Wooden mounting frame should be fixed in coordination with carpenter - furniture contractor.] - Two Ex. Fan are of heavy duty industrial for Ups room.</b>  | 5   | nos  |      |        |
| 4.6     | SITC of 48" Ceiling Fan with fan step socket modular regulator, Max. 3 feet Fan Rode, Anchor Fastner, etc. (WHITE COLOUR - BEE 5 star labeled ceiling fan Alluminium body and copper winding.) ( Orient PSFO or Equivalent approved make in Crompton / Havells. - Model High Breeze Plus BEE 5 Star labeled ceiling fan , Aluminium body , copper winding .).  | 5   | nos  |      |        |
| 4.7     | SITC of 1 x 18W led batten light fixture (T-5) with electronic driver and tube complete with necessary hardwares, etc and per watt lumens output must be above 120/watt and 90%lumems maintaiance for 90% of life with input voltage 90-270v ac 50hz operational without affecting the life, input mov.gtd protection in driver for above 270v protection. and 2 years waranty.LED Batten Comprises of Thermally conductive material. Pre-wired with high efficiency electronic driver. High translucent frosted diffuser gets glare free, smooth light distribution. ( Cormpton / GE/ Philips / Havells / Wipro make) .   | 8   | nos  |      |        |
| 4.8     | SITC of 450 mm sweep wall mounted fan with metal body, metal stand, guard and blade, 6 a. 3 pin top <b>With on site 2 years warranty. (ALMONARD tempest mark II or equivalent make.) Wall fan with PVC body strictly rejected.</b>   | 2   | nos. |      |        |
| 4.9     | SITC of Decoretive 5 W / 6 W ( 180 lumens ) LED EYE BALL LIGHT fixture with its driver also. ( wipro make or philips or equivalent co. make). (Approved by Architrcr) basic rate of fixture Rs. 375/- . ( <b><u>This is for light in ACP work near entrance</u></b> ).   | 3   | nos  |      |        |
| C       | <b>COMPUTER POWER SUPPLY &amp; NETWORKING - TELE. SYSTEM.:</b> Phase wire must be Yellow colour for UPS O/P DB, Red colour for PDB , Neutral Wire of Black colour & Green Wire for Earthing. Color code must be maintained. Tagging from DB MCB and Switch board must be done.   |     |      |      |        |

**ELECTRICAL WORK of KHOPALA BRANCH, KHOPALA, RBO-4, Ahmedabad**

| Sr. No. | DESCRIPTION   | QTY | UNIT | RATE | AMOUNT |
|---------|---|-----|------|------|--------|
| 5       | SITC of 2 nos. of 6 A, 5 pin Sockets and 1 no. of 6 \ 16 A socket below table outlets with one 16 A switch with indicator Computer power supply with concealed company made metallic boxes or PVC flush box on walls / furniture's / trunking etc complete all respect with necessary wiring of mains of 2 no of 2.5 sq mm and 1 no of 1.5 sqmm pvc insulated copper conductor multi-stranded flexible wire with 20/25 dia. PVC conduits with accessories duly burried under floor with necessary chasing / breaking in floor and to be refinished with all necessary civil material etc. complete from UPSDB to Computer power supply boards.{Maxi. 3 computers in one circuit}. complete with necessary termination etc. complete.[ White Colour Outer Plate For These Switchboards]. <b>LOOP POINTS MUST BE OF SAME SIZED WIRES. Phase wire must be Red colour, Nutral Wire must be Black color &amp; Green Wire for Earthing. Color code must be maintained. Tagging from UPS O/P DB MCB and Switch board must be done.</b> | 12  | nos  |      |        |
| 6       | SITC of 2 nos. of 6 A, 5 pin Sockets and 1 no. of with one 6 A switches raw power supply with concealed company made metallic boxes or PVC flush box on walls / furniture's / trunking etc complete all respect with necessary wiring of mains of 2 no of 2.5 sq mm and 1 no of 1.5 sqmm pvc insulated copper conductor multi-stranded flexible wire with 20/25 dia. PVC conduits with accessories duly burried under floor with necessary chasing / breaking in floor and to be refinished with all necessary civil material etc. complete from PDB to Computer power supply boards.{Maxi. 3 Raw Power Points in one circuit}. complete with necessary termination etc. complete.. [ Black Colour Outer Plate For These Switchboards]. <b>LOOP POINTS MUST BE OF SAME SIZED WIRES. Phase wire must be Red colour, Nutral Wire must be Black color &amp; Green Wire for Earthing. Color code must be maintained. Tagging from PDB MCB and Switch board must be done. .</b>  | 6   | nos  |      |        |
| 7       | SITC of CAT 6 UTP pvc insulated copper conductor data cable of D - Link with 20/25 dia. PVC conduits with accessories duly burried under floor with necessary chasing / breaking in floor and to be refinished with all necessary civil material etc. or to be cleated on wall / ceiling with saddles / spacer etc. necessary termination etc. with ferrule numbering at both ends of each piece of cable complete. <b>[ 2 Lines from data rack to new krone nr. ele. panel ]</b> .   | 60  | mtr  |      |        |
| 8       | SITC of CAT 6, RJ 45 information outlet (I/O) of D-link mke with front modular cover plate, flush box metallic or PVC for trucking system etc. complete with terminations etc complete.with Providing, installing, testing, commissioning of CAT 6 UTP pvc insulated copper conductor data cable of D-link make with 20/25 dia. PVC conduits with accessories duly burried under floor with necessary chasing / breaking in floor and to be refinished with all necessary civil material etc. or to be cleated on wall / ceiling with saddles / spacer etc. necessary termination etc. with ferrule numbering at both ends of each of piece of cable etc. complete as per the requirement from data rack to I/O points below tables. etc. <b>( One for LCD &amp; Two for ATM &amp; one for IP phone in BM cabin). Dual jack plate will not be allowed. Cross Ferruling need to be provided for each point. on Data point tagging must be done).</b>   | 12  | nos  |      |        |
| 9       | SITC of 12 U metal rack for computer clamping switch etc complete with Tray Mounting Fan + power supply board. <b>Bank's hardware - port switch / patch panel must be installed by ele. Contractor in this rack. - ( make : D Link / Digi Link / Elixer ).</b>  | 1   | nos  |      |        |

**ELECTRICAL WORK of KHOPALA BRANCH, KHOPALA, RBO-4, Ahmedabad**

| Sr. No.  | DESCRIPTION  | QTY | UNIT | RATE | AMOUNT |
|----------|--|-----|------|------|--------|
| 10       | SITC of 24 port patch panel for computers mounting in metal rack. (make : D Link / Digi Link ).  | 1   | nos  |      |        |
| 11       | Supply & fixing the Patch cord 1 mtr. Long (factory built) .-When supplying , then first ask to BM / Consultant / Architect / Bank Authority.  | 12  | nos  |      |        |
| 12       | Supply & fixing the Patch cord 2 mtr. Long (factory built) .-When supplying , then first ask to BM / Consultant / Architect / Bank Authority.  | 6   | nos  |      |        |
| 13       | SITC of telephone point with Telephone socket outlets of RJ 11 of approved make with company made concealed boxes in walls / furniture's etc. complete with Providing, installing, testing, commissioning of 2 pair of 0.51 cross section pvc insulated copper conductor telephone wire of ITI approved with 20/25 dia. PVC conduits with accessories duly burried under floor with necessary chasing / breaking in floor and to be refinished with all necessary civil material etc. or to be cleated on wall / ceiling with saddles / spacer etc. necessary termination etc. complete.from krone box to tele. RJ - 11 sockets below tables. etc.- for Intercom / fax / direct Tele. facility. Cross Ferruling need to be provided for each point. on Telephone point tagging must be done. | 7   | nos  |      |        |
| 14       | SITC of <b>10 pair krone</b> telephone tag block duly enclosed in sheet <b>metal powder coated box with locking arrangement complete with necessary terminations.</b>  | 1   | nos  |      |        |
| <b>D</b> | <b>DISTRIBUTION BOARD AND PANELS :</b>   |     |      |      |        |
| 15       | SITC of metallic double door type distribution board with all necessary connection complete to be installed concealed in wall / surface mount complete to the satisfaction of the Engineer in charge. <b>The DB should be of same make as MCB make.</b>  |     |      |      |        |
| 15.1     | 4 - WAY TPN DB : ( <b>LDB - PPI DB.</b> ) . All MCB should be ' B ' type.  | 1   | nos  |      |        |
|          | incoming : 40 A FP MCB - 1 NO.   |     |      |      |        |
|          | outgoing : 25 A DP RCCB, 100 mA - 3 NO .   |     |      |      |        |
|          | outgoing : 6 to 20 A SP MCB (6 nos).   |     |      |      |        |
| 15.2     | 4 - WAY TPN DB : ( <b>PDB - PPI DB.</b> ) . All MCB should be ' C ' type.  | 1   | nos  |      |        |
|          | incoming : 63 A FP MCB - 1 NO .  |     |      |      |        |
|          | outgoing : 40 A DP RCCB, 100 mA - 3 NO .   |     |      |      |        |
|          | outgoing : 10 to 20 A SP MCB (3 nos ) for raw power points.  |     |      |      |        |
|          | outgoing : 10 to 20 A SP MCB (3 nos ) for 6/16 A power point .   |     |      |      |        |
| 15.3     | 4 - WAY TPN DB : ( <b>ACDB</b> ) . All MCB should be ' C ' type.   | 1   | nos  |      |        |
|          | incoming : 63 A FP MCB - 1 NO .  |     |      |      |        |
|          | outgoing : 20 A / 25 A DP MCB (4 nos ) for HI- WALL SPLIT AC points.   |     |      |      |        |
| 15.4     | 6 WAY SPN DB : <b>UPS DB - OUTPUT</b> - branch . - All MCBs must be C Type Characteristic.   | 1   | nos  |      |        |
|          | incoming : 40 A DP 100 mA RCCB, 100 mA.  |     |      |      |        |
|          | outgoing : 10 to 20 A SP MCB ( 4 nos ) .   |     |      |      |        |

**ELECTRICAL WORK of KHOPALA BRANCH, KHOPALA, RBO-4, Ahmedabad**

| Sr. No. | DESCRIPTION  | QTY | UNIT | RATE | AMOUNT |
|---------|--|-----|------|------|--------|
| 15.5    | 4 WAY SPN DB . (For essential ups points - <b>UPS O/P DB.</b> ) - branch. - in UPS ROOM.   | 1   | nos  |      |        |
|         | outgoing : 16 A. DP MCB - 1 NO FOR UPS OUTPUT.   |     |      |      |        |
|         | outgoing : 10 A / 20 A. SP MCB - 2 NO FOR essential ups points - DATA RACK / FIRE PANEL / CCTV NVR PTS.  |     |      |      |        |
| 15.6    | 4 WAY SPN DB . (For <b>UPS O/P DB</b> IN UPS ROOM).  | 1   | nos  |      |        |
|         | outgoing : 40 A. DP MCB - 1 NO FOR UPS OUTPUT.   |     |      |      |        |
|         | outgoing : 25 A. DP MCB - 1 NO FOR UPS OUTPUT.   |     |      |      |        |
| 15.7    | <b>UPS INPUT</b> - 12 WAY SPN DB (For all computers ). - All MCBs must be C Type Characteristic.   | 1   | nos  |      |        |
|         | incoming : 40 A FP MCB - 1 NO FOR 3 - phase UPS.(big) .  |     |      |      |        |
|         | outgoing : 40 A. DP MCB - 1 NO FOR INVERTER OUTPUT.  |     |      |      |        |
|         | outgoing : 10 A SP MCB - 1 NO FOR UPS ROOM LIGHTING.   |     |      |      |        |
| 16      | SITC of 40 A FP changeover switch - mcb type (C - Curve) with powder coated compny made metallic double door sheet stell enclosure complete for inverter supply to LDB - check SLD. THE ENCLOSURE SHOULD BE SAME MAKE AS MCB MAKE.   | 1   | nos  |      |        |
| 17      | SITC of <b>100A FP MCCB- C&amp;S Make CSE1N100ETM4P-100A ( 36KA)</b> (1 No.) with ( <b>Ics =100% Icu., confirmed to IS / IEC 60947 -2 adujstable Ir rating from 0.7 to 1 )</b> Unit M. S. compartment enclosure IP65 with hinged door & locking arrangement duly fabricated from 18 SWG sheet metal box duly painted with one coat of red-oxide paint and two coats of approved enamell paints with 100A OPEN TYPE FP MCCB UNIT <b>with Phase indicator lamps phase wise</b> , control fuses & wooden back complete. THIS WILL BE INSTALLED NEAR MAIN DOOR - INSIDE OR OUTSIDE - OF THE BANK. ( first ask to BM / Consultant / Architect / Bank Authority. | 1   | nos  |      |        |
| 18      | SITC of Main panels as per drawing and specifications. Panel should be dust and vermin proof. Panel shall be fabricated from 14/ 16 SWG CRCA sheet metal duly powder coated of approved paints. <b>Panel should be as per the sepecifications of ERDA/CPRI. fabrication, Switch gear installation. Internal wiring and Test Certificate from Manufacturer to be submitted. - All MCBs must be C Type Characteristic. Panel Drawing Need to be approved by Electrical Consultanat / Bank's Engineer before starting work. READ SLD CAREFULLY.</b>   |     |      |      |        |
|         | <b>MAIN PANEL :</b>  | 1   | nos  |      |        |
|         | <b>Incoming feeder : 100 A C&amp;S Make CSE1N100ETM4P-100A (1 No.). The MCCB should have inbuilt Earth Fault &amp; Nutral Overload Protection with Power Supply &amp; Display Module for Metering &amp; Fault Recording.</b>   |     |      |      |        |
|         | Incoming feeder : 80 A C&S Make CSE1N80ETM4P-80A (1 No.). REGULAR POWER.   |     |      |      |        |
|         | Incoming feeder : 63 A C&S Make CSE1N63ETM4P-63A (1 No.). - ESSENTIAL POWER.   |     |      |      |        |
|         | * 63 A, FP Change over switch (1 No.). - ESSENTIAL POWER.  |     |      |      |        |
|         | * 80 A, FP Change over switch (1 No.). REGULAR POWER.  |     |      |      |        |
|         | * 125 AMP. 500 Volts, 3 phase 50 Hz FP <b>Alu.</b> bus bars of suitable length -Current ratio shall be 1 sq mm = 1.2 A.  |     |      |      |        |

**ELECTRICAL WORK of KHOPALA BRANCH, KHOPALA, RBO-4, Ahmedabad**

| Sr. No.  | DESCRIPTION   | QTY | UNIT | RATE | AMOUNT |
|----------|---|-----|------|------|--------|
|          | * 80 AMP. 500 Volts, 3 phase 50 Hz FP <b>Alu.</b> bus bars of suitable length -Current ratio shall be 1 sq mm = 1.2 A.<br>* Digital AVF Meter with control fuses. C.T. shall be of 15VA class 1 type and shall be resin cast type.<br>* Phase indicator lamps phase wise.<br>* <b>Outgoing feeder:</b><br>* Timer of L & T make Cat. No. 67DDTO digicom Timer with 16A. 4P contactor / Theben make Cat no. SUL 180 a - T180 0 001 ANALOG Timer with L & T make contactor MNX 18 ( operating coil voltage 230V, 50 Hz). (24 hrs).- <b>1 No for signage light.</b><br>* 25 A DP MCB (1 no - Sign board for branch).<br>* 40 A FP MCB (1 NO - LDB ).<br>* 63 A FP MCB (1 NO - PDB ).<br>* 63 A FP MCB (1 NO - ACDB).<br>* 40 A FP MCB (1 NO - UPSDB ).<br>* 40 A FP MCB (1 NO - SPARE DB). |     |      |      |        |
| <b>E</b> | <b>EARTHING SYSTEM:</b>   |     |      |      |        |
| 19       | SITC of Earthing Pit with all necessary material and making masonry kundi, watering arrangement etc complete as per ISI 3043-1987 ( <b>FOLLOWING ITEMS MAY OPERATE</b> ). <b>Resistivity as per IEC / IS. ( 3 years Manufacturer Warranty. Earthing Certificate Need to Attached). ( At the Time of buried of earthing Photograph must be taken Without Photographic Proof Earthing Will be Rejected. Earthing Rod Photo Must be attached with Bill.). Earthing need to measure at Site and it should be less than 5 Ohm. If found more than 5 ohm than will be rejected. Earthing Pit Must be Provided for both Cu as well as GI earthpit.</b>   |     |      |      |        |
| 19.1     | ECO SAFE environment friendly electrical grounding system with T-193- Copper electrode used upto 11 KV, having 50mm dia. of outer pipe and 25 mm dia. of inner pipe and length of 3mtrs with 50kg Back Fill Compound as per UL 476, of Powerfill Eco friendly electrical grounding backfill compound and clamp (UPS ) - Chemical CU Earthing) ERDA & NSIC approved, E link or ETP MAKE or ASHLOK MAKE. Any other make will not be consider. - Cu. ( 1 for UPS & 1 for DB - MAIN PANEL. ) .  | 2   | nos  |      |        |
| 20       | SITC and jointing of following wire / strip / earth cable on walls, ceiling etc. With necessary non rusting clamps, washers, nuts and bolts etc complete.   |     |      |      |        |
| 20.1     | SITC of 16.0 sq. mm. Cu. Flexible wire with 20 / 25 mm dia. PVC rigid conduit duly cleated / concealed / burried in floor etc. complete From Cu. earthing pit to Main Panel + From Cu. Earthpit to UPS I / P DB.  | 30  | Rmt  |      |        |
| 20.2     | SITC of 4.0 sq. mm. Cu. Flexible wire with 20 mm dia. PVC rigid conduit duly cleated / concealed / burried in floor etc. complete for all DBS, AC outdoor units, etc.   | 20  | Rmt  |      |        |

**ELECTRICAL WORK of KHOPALA BRANCH, KHOPALA, RBO-4, Ahmedabad**

| Sr. No.  | DESCRIPTION  | QTY | UNIT | RATE | AMOUNT |
|----------|--|-----|------|------|--------|
| <b>F</b> | <b>CABLES &amp; CABLE TERMINATIONS:</b>  |     |      |      |        |
| 21       | Supply, Laying, installation, testing and commissioning of following sizes of PVC insulated PVC sheathed copper / aluminum conductor armoured cable to be laying in existing cable trench or to be laid in existing pipes of with necessary clamps, spacers with cleating on wall ceiling etc. complete to the satisfaction of EIC. All types of cable excavation works should be in contractor's scope.( LENTH TO BE VERIFY AT SITE ) with end termination of following PVC insulated armoured cables including supply and fixing of brass single compression type cable glands and crimping type aluminum / copper lugs suitable for terminations of armoured cables of following overall diameters, incl. |     |      |      |        |
| 21.1     | 3 C x 2.5 sq. mm Cu . Conductor YWY cable. (for Signboard ).   | 10  | mtr  |      |        |
| 21.2     | 4 C x 6.0 sq. mm Cu. Conductor YWY cable. (Main Panel to UPS I/P DB ).   | 25  | mtr  |      |        |
| 21.3     | 4 C x 16.0 sq mm Alu. Conductor AYFY cable. ( Main Panel to LDB, PDB, AC DB. ) .   | 15  | mtr  |      |        |
| 21.4     | 3.5 C x 50.0 sq. mm Alu. Conductor AYFY cable. (main cable from Panel to main mccb nr. energy meter) (LENGTH as per site contition) .  | 25  | mtr  |      |        |
| 21.5     | 25.0 sq. mm single core Cu. wire supply & laying for main load wire from meter to main switch in flexible pipe. <b>if required.</b>  | 6   | mtr  |      |        |
| 21.6     | 3 C X 6.0 sq. mm flexible Cu. cable with 20 mm/25 mm dia PVC rigid conduits 1.5 mm thick ISI mark . ( UPS to UPS O/P DB & UPS I/P DB to UPS). - for branch.  | 36  | mtr  |      |        |
| 21.7     | 3 C X 6.0 sq. mm flexible Cu. cable with 20 mm/25 mm dia PVC rigid conduits 1.5 mm thick ISI mark . ( INVERTER to MCB CHANGEOVER & UPS I/P DB to INVERTER - for INVERTER ). - for branch.  | 33  | mtr  |      |        |
| 21.8     | 3 C X 4.0 sq. mm flexible Cu. cable with 20 mm/25 mm dia PVC rigid conduits 1.5 mm thick ISI mark . ( ups o/p db in ups room to essential ups o/p db in ups room.).  | 3   | mtr  |      |        |
| <b>G</b> | <b>MISCELLANEOUS ITEMS :</b>   |     |      |      |        |
| 22       | SITC of 300 x 300 x 40 mm size GI box duly fabricated from 18 SWG m.s. sheet with top cover of s. s. sheet complete with necessary knock outs at all the sides of box for conduit entries duly fixed in floor, including breaking in floor and re-finished the same etc. complete (Wire Draw Box).   | 5   | nos  |      |        |
| 23       | SITC of 150 x 150 x 40 mm size GI box duly fabricated from 18 SWG m.s. sheet with top cover of s. s. sheet complete with necessary knock outs at all the sides of box for conduit entries duly fixed in floor, including breaking in floor and re-finished the same etc. complete (Wire Draw Box).   | 2   | nos  |      |        |
| 24       | SITC of 2.5 sq. mm. 3 core flexible cable of approved make (3 mtr. Length) with heavy duty industrial pvc flexible pipe & 15 amp. 3 pin top of approved make for the supply of LOCKER ROOM, CASH ROOM.   | 3   | nos  |      |        |
| 25       | SITC of CABLE TV cable line with proper fixing and connecting with modular Co-Axial TV Socket. - 1 run.  | 20  | mtr  |      |        |

**ELECTRICAL WORK of KHOPALA BRANCH, KHOPALA, RBO-4, Ahmedabad**

| Sr. No. | DESCRIPTION   | QTY | UNIT | RATE | AMOUNT |
|---------|---|-----|------|------|--------|
| 26      | SITC of 24 Hr, 7 days A/C timer with 2 nos of DP power contactor of M.D.S, L & T , SEIMENS, THEBEN ( indoasian) Make. All enclosed in sheet steel powder coated enclosure of 200 X 200 mm complete with all necessary termination for UPS room ex fan supply. <b><u>Here Ready made Cyclic Timer Will not be permitted. - to be installed in ups room.</u></b>  | 1   | nos  |      |        |
| 27      | Supply & laying of the empty conduit . - 25 mm.   | 35  | mtr  |      |        |
| 28      | Laisioning work ( addition Load ) WITH Electric suppply Co. in branch & Apporoval and Necessary certificate. Contrctor must submit latest light bill + load sheet ( duly signed ) with final bill. Also check where load wires from ele. Supply vij co feeder to meter box must be carried full lod of branch & submit report.  | 1   | job  |      |        |
| 29      | Providing necessary plug points ( <b>3 boards - each including 25 DP RCCB, 30 mA + 3 nos switches &amp; 3 nos plugs, 16 a switch &amp; 16 a plug</b> ) & light points for tube lights (including nesssry wiring) at various locations as required by various contractors for execution of various works / to run equipments such as drill / cutter etc. during the entire execution process. The accessaories used for this purpose shall be of temp. nature (anchor piano or eq.) & the contractor has to take back the same on completion of the project. The supply for this shall be taken from the temporary connection provided at / from nearby general meter under co.ordintion with the LANDLORD. & also providing temporary power supply for computers and data connection for computers with wiring, switchboard, Comp. I/O Points,etc. for smoothly running of the branch with removing & reshifting of the computers , printers, etc. bank hardware accessories. | 1   | job  |      |        |
|         | <b><u>GRAND TOTAL :::</u></b>   |     |      |      |        |