

RENOVATION OF WAKKA BRANCH
BOQ for Electrical Installation Works

SL No	DESCRIPTION	UOM	QTY	Rate (Rs.) (Exclusive of GST on work contract)	Amount (Rs.) (Exclusive of GST on work contract)
1	<p>a. Main Panel :- Supplying, Installing, testing and commissioning of factory fabricated 2MM thick CRCA, floor mounted cubicle type distribution Panel Board with 150 MM X 75 MM X 6MM ISMC base channel, suitable for 415 V TPN comprising of 300A suitable copper bus bars with color coded heat shrink insulation with the followings:</p> <p>160 A, 4P MCCB, 50 kA with overvoltage protection as incomer, R-Y-B LED indicating lamps, Digital multifunction meter of minimum size 150 MM X 150 MM to measure Voltage, Current, PF etc with all accessories</p> <p>Outgoing: 63 A 4P MCCB, 35kA for UPS - 1 Nos for UPS 100 Amp 4P MCCB, 35kA for Raw power - 1 Nos, 63 Amp TPN MCCB, 35 kA - 1 Nos. for External equipment and raw Power. All MCCBs are strictly as specified above only.</p> <p>All outgoing must be in compartmentalized chamber fully isolated with 2 mm thick CRCA and 3 mm steel channel painted with 2 coats of red oxide primer paint followed by finishing paint with interconnection etc. as required.</p>	Set	1		
2	<p>Sub-main line:- Wiring in MS conduit of IS specification of Proper size with core PVC insulated stranded copper wire 11KV grade (Finolex/Havells/Polycab/ RR Kabel/ Richa/KEI or equivalent) and with supply, installation, commissioning of all the materials required including proper termination, connection in complete as required from main DB to various DBs:-</p>				
i)	with 3nos 4sq.mm (1ECC)	RM	110		
ii)	with 3nos 6sq.mm (1ECC)	RM	60		
3	<p>Supply, installation, testing and commissioning of distribution board manufactures made sheet steel enclosure With the following MCBs (DB, MCB and MCCB Make- Legrands/ Havells/ L&T/ SIEMENS or equivalent) and connecting the same to the system.</p>				
i)	Computer/Raw power DB, SPN double door with 40A (30mA)DP RCCB as incomer & 5nos 10A SP MCB as outgoing.	No.s	2		
ii)	DB with 32A DP MCB.	No.s	4		
iii)	DB with 16A DP MCB. (Security and fire)	No.s	2		
iv)	DB with 32A DP RCCB.	No.s	2		
v)	DB with 32A MCB Changeover	Nos.	1		
vi)	Modular 5 pin Socket With 20A SP MCB protected switch (Each Table for Power Plug).	No.s	6		
viii)	VTPN Double Door Distribution Board with 63A 4 Pole MCCB (36kA) as incomer and 1 No. of 40A TP MCB, 6 nos. of 32 A SP MCB and 2 nos of 16A SP MCB at out going	Set	1		
viii)	VTPN Double Door Distribution Board with 100A 4 Pole MCCB (36kA) as incomer and 8 nos. of 32 A SP MCB and 2 nos of 16A SP MCB at out going	Set	1		
ix)	Light DB SPN double door with 40A (30mA)DP RCCB as incomer & 5 nos 10A SP MCB as outgoing.	No.s	2		

SL No	DESCRIPTION	UOM	QTY	Rate (Rs.) (Exclusive of GST on work contract)	Amount (Rs.) (Exclusive of GST on work contract)
4	Supplying, installing and commissioning of PVC Armored cable complete with proper cable glands and two nos. of 8SWG GI wire (Havell's/Richa/RR kebel/KEI or equivalent) alongwith all the other materials required including proper connection in complete as required from main Panel,Power Distribution Board to various DBs .				
i)	With 3.5 core x 35 sq. mm cable	RM	80		
5	Supply, installing and commissioning of earth station including digging and refilling back the pit with black soil and with 3.15mm x300mm size copper plate duly finned through out the surface of the plate, placed at least 1.5Mtr,below the ground level with 2nos 10sq.mm PVC insulated stranded copper conductor in 20mm GI pipe, fixed to the plate and providing 40mm,2mtr,long GI pipe with reducer and funnel at top for watering pipe with supplying and laying earth continuity wire of 2x10sq.mm copper stranded PVC green color in heavy duty MS conduit on the wall from earth plate to starting point of the line earth connector with proper earth pit.	Nos.	4		
	i) Supplying and fixing 25x3 mm copper strip, insulated by heat pressurized heavy gauge PVC sleeve, duly jointed by full lap brazing and drawn underground in 40 mm class B GI pipe from the inspection pit to the inside of the branch premises.	RM	20		
	ii)Supplying and fixing 2X8 SWG dia copper earth wire in PVC conduit on surface or in recess for loop earthing from panel to DB	RM	60		
6	Computer/Raw Power point wiring in MS conduit of IS specification of proper size with 3nos 2.5sq.mm single core PVC insulated stranded copper wire 1.1KV grade(Finolex/Havells/Polycab/ RR Kabel/ Richa/KEI or equivalent) and with all material supply installation and commissioning complete from /PDB(Raw) .The wiring shall be carried out on surface above false ceiling by chiseling the existing surface and plastering the same with cement etc. after fixing the MS conduit with all accessories like saddles screws, bends T-joint etc. 2 coats of painting Matching to the surface including supply installing, testing, commissioning of modular plate type switch and socket (Legrands / MK or equivalent) for computer terminal on sheet steel enclosure (cadmium plated),duly fitted with screw to the steel conduit and fixed to the wall partition furniture with all interconnection and proper earthing .All the opening shall be covered with blank plate and be sealed to make the box vermin proof.B48(maximum three points in single circuit)				
i)	With 3nos 6A socket with single 16A switch.	No.s	12		
ii)	With 2nos 16A socket with individual switch.	No.s	8		
iii)	With 1nos 16A socket with individual switch.	No.s	5		
7	Supply, installation testing and commissioning of recessed mounted circular LED downlighter with 15W LED lamp. Make :- Bajaj/Havels/Phillips/Wipro/Crompton or equivalent. (Model: Havells INTEGRANXTDLR15WLED857S TR or Equivalent specification)	Nos	20		

SL No	DESCRIPTION	UOM	QTY	Rate (Rs.) (Exclusive of GST on work contract)	Amount (Rs.) (Exclusive of GST on work contract)
8	Supply, installation testing and commissioning of surface mounted circular LED downlighter with 15W LED lamp. Make :- Bajaj/Havels/Phillips/Wipro/Crompton or equivalent. (Model: Havells GLOWDLS15WLED830S or Equivalent Specification)	Nos	5		
9	Supply, installation testing and commissioning of recessed type LED luminaire with complete PMMA Difuser with 36 W LED lamp (size 2"X 2")(Model:Plano or equivalent) . Make : Bajaj/ Havels/ Phillips/ Wipro/ Crompton or equivalent	Nos	10		
10	Supply installation testing and commissioning of LED batten Single Tube light fittings with 20W (Model: Havells LUMILINEBS20WLED865SPCWH or equivalent Specification) with glare free light distribution wall mounted at ceiling/false ceiling level/. Make :- Bajaj/ Havels/ Phillips/ Wipro/ Crompton or equivalent	Nos	18		
11	Supply and installation of Wall Mounted fan 400 mm full Metallic body and metallic Blade, 1400 rpm crompton/ bajaj/ usha/ orient make	No.s	4		
13	Supply and installation of heavy duty Exhaust Fan 300 mm crompton/ bajaj/ usha/ havells make	No.s	3		
14	Supplying, installation,testing & commissioning of Security light with 25W LED lamps with pressure die cast housing with epoxy coated dark graphite grey colour finish and prismatic polycarbonates cover with individual LED lenses, including necessary GI bracket with clamp. Make :- Bajaj/ Havels/ Phillips/ Wipro/ Crompton or equivalent	Nos.	4		
15	Wiring for light/fan/exhaust fan points using 3 X 1.5 1.1 kV grade PVC insulated stranded copper conductor wire (Finolex/ Havell's/ Richa/ RR kebel/ KEI or equivalent) for phase, neutral and earth in 25 mm dia heavy duty MS conduit along with associated accessories like MS junction boxes, bends, saddles, screws et. concealed in wall, floor, under flooring, below false ceiling or on surface as well as suspended from ceiling with 25mm X 3 mm MS flat suspenders duly painted above false ceiling from individual light/Fan/Exhaust Fan point outlet. etc. to individual modular type switch boards, 10 Amp modular plate type switches etc.(MK/Legrand's/Havell's or equivalent), as required complete including circuit wiring with 3 X 2.5 sqmm. 1.1 kV grade PVC insulated stranded copper conductor wire and as per site requirement and as instructed by SBIMS Engineer.				
i)	Light/fan point (Two downlighter/ 2"X 2" recessed light fittings to be connected through one point)	No.s	30		
ii)	Light/fan point (four downlighter/ two 2"X 2" recessed light fittings to be connected through one point)		15		
iii)	6A socket & switch at same board	No.s	8		
iv)	16A, 5 pin industrial plug & Socket with 25 A MCB protected (for Safe room & Record room)	Nos.	2		
v)	Modular type with 6A SP MCB for Exhaust fan and wall fan	No.s	9		
	Total				

GST on work contract will be extra as applicable.